



12722 (ZW4005)

**Z-Wave, In-Wall Smart Switch
(Interchangeable Paddles)**



Key Features

- Turn the connected device On/Off manually or via Z-Wave remote control
- May be used in single pole installation or with up to four GE model 12723 Add-on switches in 3, 4, 5 or 6-way wiring configurations
- Blue LED indicates switch location in a dark room
- Can be Included in multiple Groups and Scenes
- Supports Advanced Configuration; LED status, Invert switch (if unit is installed upside down)
- Screw Terminal installation; requires wiring connections for Line (Hot), Load, Neutral, and Ground. Traveler wire required for multi pole installation
- Use a standard-size wall plate for single gang installations (wall plate not included); Multi-gang box option available (removable 'side wings')
- Interchangeable Paddle switch: White & light almond paddle included in package
- LED can be enabled/disabled manually
- Inline traveler circuit protection

SPECIFICATIONS

Power: 120 VAC, 60 Hz.

Signal (Frequency): 908.42 MHz.

Load ratings:

Incandescent - Minimum Load: 40W, Maximum Load: 960W

Motor – 1/2HP

Resistive – 1800W

Range: Up to 100 feet line of sight between the Wireless Controller and the closest Z-Wave receiver module.

Operating Temperature Range: 32-104° F (0-40° C)

For indoor use only.

cUL Listed

Complies with FCC and Industry Canada regulations

JASCO Products

10 E. Memorial Rd

Oklahoma City, OK 73114

www.jascoproducts.com

www.easyzwave.com

Z-Wave is a registered US trademark of Sigma Designs

The GE logo is a registered trademark of General Electric Company and is used under license to JASCO products Company, LLC

The images, product information and specifications listed in this document are subject to change